

Portable Power Inverters

Bulletin	UK	Export	Vap	Issued
1173	YES	NO	YES	12 th April 2010

12v 300w Power Inverter (Part No. VLC1040)

The 12v, 300w single socket inverter is simple and safe to use on equipment rated up to 300w such as laptop computers, camcorders, stereos, small fridges, small power tools and many other applications. The unit can be powered directly from the battery or via the vehicles 12v "cigarette lighter" socket.

Maximum power rating (watts)	300 (5 mins)
Peak power (watts) 0.01 seconds	600
Stand by current (amps)	0.25
Waveform	Modified Sine
Efficiency	90%
Input voltage range	10-15 volts DC
240v AC socket (BS approved)	3 pin
Fuse (amps)	40
Weight (kgs)	0.88
Continuous power rating (watts)	240w (4 hours)
Cable length	0.5m



Suitable for...

- ✓ Laptops
- ✓ Small Power Tools
- ✓ Battery Chargers
- ✓ Small Fridges
- ✓ Lights
- ✓ Camcorders



12v 2100w (2.1Kw) Power Inverter (Part No. VLC1041)

High quality inverter, ideal for the professional user requiring mains power for heavy duty applications. 12 hours constant use at 2100w. Includes wireless remote control. Digital display shows application wattage and battery voltage.

Maximum power rating (watts)	2100
Peak power (watts) 0.01 seconds	4200
Standby current (amps)	0.45
Waveform	Modified Sine
Efficiency	90%
Input voltage range	10-15 volts DC
240v AC socket (BS approved)	3 pin
Fuse (amps)	8 X 40
Weight (kgs)	6.61
Certification	CE approved
Continuous power rating	2100w (12 hours)
Cable length	1.0m



Suitable for...

- ✓ Power Tools
- ✓ Electro Hydraulic Swaging Machines
- ✓ Lighting and heating
- ✓ Compressors
- ✓ TV's



All Vapormatic quality replacement parts carry an industry leading **12 month parts and labour warranty**. For further information on specific items please visit www.vapormatic.com